



## DAP200

Multi-format Digital Audio Player w/ WACI NX+ hardware control. 2 Serial Ports, 4 IR/RS-232TX ports, 4 Relays and 4 DSP I/Os, IR Learner and built-in event manager. The NX-DAP allows for direct control of audio playback from the control system. Not only can any of WACI's ports be set up to trigger playback, but it can trigger a specific portion of an audio track to play, repeat, play for a fixed time or play until another event is triggered. All of the setup can be done right from the Event Manager and no external components are needed.



<b>Specifications</b>	
Size	5.80 x 4.90 x 1.90 inches
Hardware	<p>Two 10/100T LAN Ports with Auto MDX and Auto Polarity</p> <p>One IR Input Port.</p> <p>One IR Learner.</p> <p>Two 2-way RS-232/422/485 ports.</p> <p>4 IR/1-way RS-232 ports</p> <p>4 DSP ports: TTL In/Out and analog inputs and outputs - 5v to + 5v</p> <p>4 isolated low-voltage relays C-Type 24VDC @1A</p> <p>One High-speed, 2.1Gb/s card slot.</p> <p>One USB On-the-Go Port.</p> <p>One compact flash Type II slot for memory and/or 802.11b/g.</p> <p>OLED Display with 6 buttons.</p> <p>15W 12v Power Supply.</p> <p>Internal web server with built-in event manager.</p> <p>Analog audio outputs: left/right</p> <p>SPDiF digital audio output</p> <p>Event manager controlled</p> <p>Plays most digital audio file formats: WMA, MP3, WAV</p> <p>CD quality audio or better</p>

Available at:  NETWORK Spectrum®

Call: 301-733-0657

Email: [sales@networkspectrum.com](mailto:sales@networkspectrum.com)

Other products available at:

[www.networkspectrum.com/gsaschedule/](http://www.networkspectrum.com/gsaschedule/)